

### NON-CONTACT VOLTAGE DETECTOR



#### DESCRIPTION

The **LVD-15** non-contact Voltage Detector is intended to check for the presence of AC voltage, signaling the user with an intermittent tone and a flashing LED.

The non-contact Voltage Detector is used to detect voltage in outlets, lighting fixtures, circuit breakers, wires, and cables or to find a break in a wire.

#### FEATURES

1. Bright LED and audible alarm sound when voltage is present.
2. Designed for non-contact voltage detection. It's safer.
3. Can be used to find a break in a wire.
4. Flash light function.
5. ON/OFF switch for longer battery life.
6. EN61010-1 EN61326-1 IEC61000-4-2 IEC61000-4-3



#### SPECIFICATIONS

1. Voltage detection : 50V~1000V AC
2. Frequency : 50~500 Hz
3. Measurement category : CAT.III 600V
4. Indication : LED and Tone
5. Operating Conditions
  - Temperature : 0~40°C
  - Humidity : Less than 80% R.H.
  - Altitude : 2000m (6500 feet) maximum
6. Pollution degree : 2
7. Dimension : 142(L) x 28(W) x 27(D) mm
8. Weight : 45g (batteries included)
9. Power supply : 1.5V AAA battery x 2

